

OMNITRONIC DXO-26 PRO Digital controller

Digital stereo active crossover incl. PC software

Art. No.: 10356350

GTIN: 4026397177770



Features:

- 2 analog inputs and 6 analog outputs (servo-balanced XLR connectors)
- Active frequency filter with slopes up to 48 dB/octave split up the audio signal into different frequency bands
- MIDI interface
- Rs232 interface, compatible to PCs
- Incl. software editor for remote control via PC: store, transfer, and manage your presets
- 60 user programs can be memorized internally or via PC software
- Both inputs or a sum of both can be split up into a maximum of 6 frequency bands
- Up to 38 frequency bands for fine-tuning the frequency range adjustable
- Up to 635.417 ms total delay for the inputs and outputs adjustable
- Delay displayed in milliseconds, meters, feet and frame/second
- Output limiter with adjustable limits and automatic attack and release settings as overload protection for your amplifying system
- Lock function for protecting the program settings
- Phase Invert switch per output
- Switch-mode power supply
- Rack installation, 1 U

Logistic

EAN / GTIN: 4026397177770

Weight: 3,80 kg

Length: 0.52 m

Width: 0.33 m

Height: 0.08 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption: 30.00 W

Dimensions: Width: 48.3 cm
Depth: 22.3 cm

	Height: 4.45 cm
Weight:	3.6 kg
Inputs:	2, active, balanced
Gain range:	±15 dB
Input impedance:	10 kohms
Frequency range:	15-20000 Hz, ±0.25 dB
	15-40000 Hz, ±3 dB
Outputs:	6, active, balanced with automatic correction for unbalanced loading
Output impedance:	<50 mohms (electronically balanced)
Output gain range:	±21 dB
Maximum output level:	+20 dBu
Frequency range:	15-20000 Hz, ±0.25 dB
	15-40000 Hz, ±3 dB
Distorsion:	0,005 %, 20-20000 Hz
S/N-ratio:	112 dB (22-22000 Hz)
Channel separation:	80 dB (30-20000 Hz)
Filter:	
Slopes:	6, 12, 18, 24 or 48 dB/Oktave
Type:	Bessel, Butterworth or Linkwitz-Riley
Crossover frequency:	15-20000 Hz
Delay:	0~635.417 ms
Dimensions (WxHxD):	482 x 44 x 223 mm

Scope of delivery: