

## OMNITRONIC CS-406 Powered mixer

Power mixer with 6 channels

Réf. : 10050025

GTIN: 4026397183276



### Caractéristiques:

- Low-noise 6-channel mic/line mixer and amplifier with 2 x 200 W/4 ohms output power
- Adjustable digital reverb
- 6 mono input channels (XLR and 6.3 mm jack) with gain control, 2-band EQ, pan and effect control
- Insert or direct out (6.3 mm jack) per input channel
- Aux send per channel for controlling external effectors
- Adjustable effect way for controlling external effect units (aux send/return)
- Tape input and output, switchable (stereo RCA)
- Adjustable headphones output (6.3 mm jack)
- +48V phantom power, can be switched centrally
- 2 x 7-band graphic equalizer for fine-tuned sound
- Precise 5-fold stereo LED meter
- 2 Speaker outputs

### Logistique

EAN / GTIN: 4026397183276

Poids: 10,75 kg

Longueur: 0.36 m

Largeur: 0.35 m

Hauteur: 0.52 m

### Données techniques:

Alimentation électrique: 115/230 V CA, 50/60 Hz

Puissance totale de raccordement: 800,00 W

Puissance de sortie: Max. 400 W

Dimension: Largeur : 44 cm  
Profondeur : 26 cm  
Hauteur : 27,5 cm

Poids:	9,15 kg
<b>Inputs:</b>	
6 x mono	XLR or balanced 6.3 mm jacks
1 x Aux Return:	balanced 6.3 mm jack
1 x Tape In	stereo RCA
<b>Outputs:</b>	
1 x Main Out:	Speaker sockets
1 x Headphones	balanced 6.3 mm jack
1 x Aux Send:	balanced 6.3 mm jack
1 x Tape Out	stereo RCA
<b>Frequency range:</b>	
Microphone:	10-60000 Hz, $\pm 3$ dB
Mono:	10-60000 Hz, $\pm 3$ dB
Stereo:	10-55000 Hz, $\pm 3$ dB
Distortion:	0.01 %
S/N ratio:	112 dB
<b>Tone control/channel:</b>	
Treble:	$\pm 15$ dB at 12 kHz
Middle:	$\pm 15$ dB at 2.5 kHz
Bass:	$\pm 15$ dB at 80 Hz
<b>Power output sine:</b>	
Stereo 4 ohms	2 x 200 W
Dimensions (W x D x H):	440 x 260 x 275 mm

### **Contenu de la livraison:**