

INTUSONIC 4FW50T 4" Altoparlante fullrange bianco

Altoparlante da installazione 4" per musica di sottofondo 20W AES, 16 Ohm

Art.n.: 12604002

GTIN: 5060502923011



Descrizione :

The INTUCAB 4FW50T is a wideband background music speaker for indoor applications where an unobtrusive appearance and mechanical ruggedness must be combined with above-average SPL and pristine sound quality. With 16 ohms of impedance, it is perfectly suited for low-impedance applications with up to 4 speakers in parallel, and the optionally available input transformer kit makes integration with 100V systems easy as well. Catering for the ease of cabling in fixed installations, an additional 5.0mm terminal strip is provided. The mounting options include M6 and M10 mounting points, allowing for suspended mounting, truss mounting and bracket mounting. Available in black and white structural paint finish for further flexibility. For full-range applications, a combination with the INTUCAB 8SM300T Subwoofer is recommended.

Logistica

EAN / GTIN: 5060502923011

Peso : 2,15 kg

Lunghezza : 0.21 m

Larghezza : 0.20 m

Altezza : 0.20 m

Features :

- Opzione kit trasformatore 100 V (UTK20 - venduto separatamente)
- Per maggiori informazioni su questo prodotto, consultare "Download" nella scheda tecnica

Dati tecnici :

Capacità di carico:	Nominale: 20W AES Programma: 40W
Intervallo di frequenza:	100 - 15000 Hz
Sensibilità:	84 dB (1W/1m)
Pressione acustica massima:	102,5 dB

Impedenza:	16 Ohm
Sistema di registrazione:	Filettatura M10 3x Filettatura M6
Collegamenti:	2 x Presa da incasso per altoparlanti (F) 1 x morsetto a vite
Altoparlante:	4" altoparlante a banda larga
Tipo di altoparlante:	Cassa compatta
Tipologia di struttura:	Cassa chiusa
Materiale:	MDF (pannello di fibra a media densità), 12 mm
Colore:	Bianco, Superficie strutturata, verniciato
Misure:	Larghezza: 13 cm Profondità: 16 cm Altezza: 13,8 cm
Peso:	1,95 kg

Contenuto della confezione:

1 x testata
 1 x Manuale d'uso
 1 x morsetto a vite
 3 x Occhiello per corda di sicurezza
 1 x adattatore