



Descrizione :

The INTUWORX DLA26 is a stereo 2-in-6 splitter allowing to build large multi-zone systems fed with different levels of the same two selectable input signals. Every output/zone features a 2-band EQ, volume control and overload LED on the front panel, and can be switched to mono on the rear panel if required. Likewise, a 100Hz HPF can be engaged per zone on the rear panel, to cater for connected speaker systems potentially unable to reproduce very low frequencies. Limiting the range of the front panel volume controls, additional rear-panel controls allow to set the maximum volume for every output/zone. Aside from its splitter/zoner functions, the DLA26 also adds versatility by allowing to feed a signal from a mobile device via its front-panel 3.5mm input, and by its additional emergency features which include a mute contact and an auto-sensing emergency priority input. The DLA26 is the perfect companion to single-output mixers to build multi-zone systems.

Features :

- Custodia per mixer
- Per maggiori informazioni su questo prodotto, consultare "Download" nella scheda tecnica

Dati tecnici :

Alimentazione elettrica:	115/230 V AC, 50/60 Hz
Potenza totale installata:	Massimo 12 W
Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite Dispositivi a freddo (M) cavo di alimentazione con spina di protezione (in dotazione)

Logistica

EAN / GTIN: 5060502923233
Peso : 3,60 kg
Lunghezza : 0.54 m
Larghezza : 0.33 m
Altezza : 0.10 m

Rapporto segnale-rumore:	>82 dB
Distorsione armonica totale:	<0,06 % a 1 kHz
Attenuazione di diafonia:	>72 dB
Livello massimo:	Ingresso: +17,8 dBu
Colore:	Nero
Struttura della custodia:	Custodia per mixer
Misure:	Larghezza: 48,3 cm Profondità: 22 cm Altezza: 4,4 cm
Peso:	3,05 kg

Contenuto della confezione:

1 x Manuale d'uso
 1 x Dispositivo
 1 x Cavo di rete/Cavo di alimentazione
 7 x morsetto a vite
 1 x connettore
 4 x piede