



Features :

Logistica

EUROLITE AKKU UP-4 HCL Spot WDMX bk

LED Uplight with 4 x 12 W 6in1 LED & wireless DMX receiver (Wireless Solution)

- Compact and bright
- Equipped with 4 x 12 W HCL (hexacolor LED) in red, green, blue, amber, white and UV
- With integrated wireless receiver for WDMX operation (Wireless Solution - made in Sweden)
- Operation via mains connection or built-in rechargeable lithium-ion battery with up to 8.5 hours operating time
- Integrated automatic charging of the battery with indicator
- Controllable via EUROLITE IR-7 remote control; included in the delivery
- With integrated folding foot for angled placement by floor installation
- DMX-controlled operation or stand-alone operation with Master/Slave function
- 6, 8 or 12 DMX channels selectable
- Functions: static colors, stepless RGBAW+UV color mixture, internal programs, dimmer, strobe effect with variable speed, sound-control
- Dimmer speed (step response) adjustable
- Adjustable microphone sensitivity
- Addressing via control panel with 4-digit LED display
- Switch-mode power supply for operation between 100 and 240 volts
- Ready for connection via included power cable with safety power plug
- Feed-through output allows to power up to 8 devices
- DMX control via any standard DMX controller

- Available in 2 housing colors: black and white
- Il dispositivo è raffreddato tramite Raffreddamento a convezione passiva
- Controllabile via stand-alone; W-DMX by wireless solution; Telecomando IR
- Senza sfarfallio
- With a beam angle of 22°

Dispositivo

- Senza fili, flessibile e versatile
- Durata di funzionamento fino a 8,5h a seconda del programma utilizzato

ROADINGER Flightcase 4x AKKU UP-4

Custodia per cassa, PRO version

- Il passaggio del cavo consente di caricare i dispositivi nella custodia
- With 4 scomparti per dispositivi
- High-quality workmanship with Legno multistrato di betulla 7 mm, marrone scuro, laminato
- Interior with Imbottitura in schiuma
- Aluminum profile frames 25mm with rounded edges
- Custodia cromata maniglia pieghevole
- 2 Cerniere di bloccaggio cromate
- 1 Serratura a farfalla di alta qualità
- Closes with a
- Piedini in gomma
- Hardware di marca
- Made in Europe
- Per maggiori informazioni su questo prodotto, consultare "Download" nella scheda tecnica

Dati tecnici :

Peso: 16,22 kg

EUROLITE AKKU UP-4 HCL Spot WDMX bk

Alimentazione elettrica:	100-240 V AC, 50/60 Hz
Potenza totale installata:	37 W
Tipo di lampada:	Lampada a LED
Raffreddamento:	Raffreddamento a convezione passiva
Attivazione:	Stand-alone; W-DMX by wireless solution; Telecomando IR
Fixtures disponibili per:	Light J; LED PC-Control 512; Light Captain
Proiezione:	Senza sfarfallio
Angolazione del fascio di luce:	22°
Angolazione del fascio di luce (1/2 picco):	22°
Angolazione del fascio di luce (1/10 di picco):	33°
Colore della custodia:	Nero
Misure:	Larghezza: 13,8 cm Profondità: 14,5 cm Altezza: 19,1 cm
Peso:	2,91 kg
Tipo di batteria:	1 x Ioni di litio 14,8 V, 6600 mAh, 97,68 Wh
Batteria:	Durata di funzionamento fino a 8,5h a seconda del programma utilizzato Tempo di ricarica 4,5h

Pila:	1 x pila a bottone 3,0 V CR2025 litio-manganese montato
Battery pack type:	Li-ion 14.8 V, 6600 mAh (97.68 Wh)
Battery operation:	8.5 hours
Recharging time:	4.5 hours
Battery remote control:	CR2025 button cell 3 V
DMX channels:	6/8/12
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
Wireless signal transmission:	2.4 GHz (ISM)
LED type:	12 W HCL
LED number:	4
Beam angle:	22°
Dimensions (L x W x H):	145 x 138 x 191 mm

ROADINGER Flightcase 4x AKKU UP-4

Carico massimo:	25 kg
Telaio in alluminio:	25 mm
Manico pieghevole:	1 Pezzo
Cerniera di bloccaggio:	2 Pezzo
Chiusura:	Serratura a farfalla: 1 Pezzo
Ausilio di trasporto:	Piedini in gomma
Uso del marchio:	Hardware di marca
Materiale:	Legno multistrato di betulla, 7 mm
Colore:	Marrone scuro, laminato
Dimensioni vano:	16 cm x 15 cm x 15,5 cm
Dimensioni interne:	33 cm x 31 cm x 15,5 cm
Misure:	Larghezza: 37 cm Profondità: 35 cm Altezza: 25,5 cm
Peso:	4,59 kg

Contenuto della confezione:

- 1 x Dispositivo
- 1 x telecomando