

## EUROLITE FD-12 DMX dimmer panel

DMX lighting controller 12 channels

Art.n.: 70063811

GTIN: 4026397298970



**L'articolo non è più disponibile.**

### Features :

- 12 channel faders with LED
- Fade time fader with LED for adjusting the step time
- Master fader with LED for adjusting the total output level
- Speed fader for adjusting the program-speed
- Flash button per channel and master-flash
- LED display of all modes
- 4 freely programmable programs with up to 84 steps each
- Controller comes with 4 pre-programmed chasers
- The programs and chasers can be called up individually or combined (CH1-2-3-4-PR-1-2-3-4)
- Dimmer: manual control of the channels via sliders
- Full On: all channels can be switched on together
- Blackout function
- Program speed adjustable via speed fader or tap sync button
- Sound-control via external signal or integrated microphone
- Only for professional use
- Sound to light via 6.3 mm jack
- Power supply via included power unit

### Logistica

EAN / GTIN: 4026397298970

Peso : 2,30 kg

Lunghezza : 0.53 m

Larghezza : 0.23 m

Altezza : 0.15 m

### Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 1,00 W

Pila: 1 x 9.0 V E block (non in dotazione)

|                             |                                                           |
|-----------------------------|-----------------------------------------------------------|
| Misure:                     | Larghezza: 41,5 cm<br>Profondità: 15 cm<br>Altezza: 7 cm  |
|                             | via 9-15 V DC, 300 mA power unit included in the delivery |
|                             | or 1 standard 9 V battery                                 |
| Battery life:               | approx. 3 hours                                           |
| Number of control channels: | 12                                                        |
| Integrated chasers:         | 4                                                         |
| Free programs:              | 4 x 84 scenes                                             |
| Sound-control:              | via built-in microphone or via audio-input                |
| Audio-input:                | Jack                                                      |
| Audio-sensitivity:          | 0.1-1 V                                                   |
| DMX512 output:              | 3-pin XLR connector                                       |
| Weight:                     | 2 kg                                                      |

### **Contenuto della confezione:**