

## OMNITRONIC PM-404 DJ Mixer

PRO 2-channel DJ mixer

Art. No.: 10006817

GTIN: 4026397313444



**The article is no longer in our assortment.**

### Description:

What is your demand?

It does not always necessarily need to be the biggest, the most expensive and most beautiful, does it? A thinking that is true of many fields. Our OMNITRONIC PM-404 DJ mixer sets an appropriate example. Because like cars, cameras or televisions, DJ-mixers do as well offer bigger and smaller versions. The own demand is the decisive factor. You need a reliable, solid standard mixer with current standard features and an appealing design? For you two input channels with gain control and a 3-way equalizer, one microphone channel with a 2-way equalizer and talkover function, a replaceable crossfader, super-smooth channel faders, a 10-digit stereo LED level meter and master level control, two switchable line/phono inputs and a headphone input of course are enough? Then the PM-404 is your choice. Because this mixer is an uncomplicated and unexpensive alternative for the home mixing area as well as for a bar with DJ. Sometimes it doesn't need more to be satisfied!

### Features:

- 2 input channels with gain control and 3-way equalizer with kill function
- Level control, 2-way equalizer and talkover button for the DJ microphone channel
- Pre-fader listening (CUE) to the stereo input channels via adjustable headphone output, with cue mix control
- Replaceable crossfader for crossfading between input channels A and B
- High-quality and super-smooth channel faders
- 10-digit stereo LED level meter and master level control
- Inputs: 2 x line/phono (stereo RCA), switchable; DJ microphone and headphones (both 6.3 mm jack)
- Outputs: master and record (both stereo RCA)
- Operation via supplied power unit

### Logistic

EAN / GTIN: 4026397313444

Weight: 3,30 kg

Length: 0.39 m

Width: 0.27 m

Height: 0.13 m

## Technical specifications:

|                        |   |
|------------------------|---|
| Power supply:          | 230 V AC, 50 Hz   |
| Power consumption:     | 5,00 W  |
| Power connection:      | Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided) |
| Frequency range:       | 20 - 20000 Hz   |
| Dimensions:            | Width: 25,5 cm<br>Depth: 26,2 cm<br>Height: 8,4 cm  |
| Weight:                | 2,8 kg  |
|                        | via supplied power unit   |
| Inputs:                |   |
| DJ microphone:         | 6.3 mm jack   |
| Minimum input voltage: | 1.5 mV RMS/ 1 kohms   |
| LINE 1-2:              | stereo RCA  |
| Minimum input voltage: | 150 mV RMS/ 270 kohms   |
| PHONO 1-2:             | stereo RCA  |
| Minimum input voltage: | 3 mV RMS/ 470 kohms   |
| Outputs:               |   |
| MASTER:                | stereo RCA  |
| Max. output level:     | +22 dBu   |
| Output voltage:        | 9 V RMS   |
| REC:                   | stereo RCA  |
| Output voltage:        | 225 mV RMS/ 5 kohms   |
| Headphones output:     | 6.3 mm stereo jack/ 16 ohms   |
| Tone control:          |   |
| 2 x High:              | -26 dB to +12 dB/ 12 kHz  |
| 2 x Middle:            | ±15 dB/ 2.5 kHz   |
| 2 x Low:               | -26 dB to +12 dB/ 80 Hz   |
| S/N ratio:             | >80 dB  |
| Distortion:            | <0.02% (line/phono)   |