

## EUROLITE EASY Show

Programmed DMX controller for over 200 spotlights from EUROLITE

Art. No.: 70064578

GTIN: 4026397675337



### Features:

- Easy-to-use DMX controller and DMX recorder
- Designed for DMX beginners with 200 programmed fixtures
- DMX recording function for your own projects, ideal for installations or rental companies
- Ideal for colored LED spotlights, KLS systems, moving lights and lighting effects
- No programming required, simply connect your spotlights and get started
- All spotlights can be freely combined to a show
- Data storage on USB flash drives
- A list of all preset devices is available at [www.steinigke.de](http://www.steinigke.de)
- Program speed adjustable; color fade adjustable; Dimmer
- Strobe effect
- 24 integrated show programs
- Direct color selection for 12 preset colors
- Preprogrammed 24 scenes/chases and 12 cues
- Control via DMX; sound to light via microphone; QuickDMX via USB (optional)
- Monochrome LCD display
- Desktop console housing
- For application areas such as: Clubs/dancing school; party room; mobile djs / entertainer; restaurants, bars and hotels
- Silent operation

### Logistic

EAN / GTIN: 4026397675337

Weight: 1,64 kg

Length: 0.31 m

Width: 0.24 m

Height: 0.11 m

### Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz  
5V DC 250 mA

Power consumption:	1.25 W
Power connection:	Mains input via USB C (W) mounting version power supply cord with AC adapter
Programs:	Preprogrammed 24 scenes/chases and 12 cues
DMX input:	3-pin XLR (M) mounting version
DMX output:	3-pin XLR (F) mounting version
Control:	DMX; sound to light via microphone; QuickDMX via USB (optional)
Housing color:	Black
Display type:	Monochrome LCD display
Available storage media:	USB devices
Housing design:	Desktop console housing
Dimensions:	Width: 28.0 cm Depth: 14.5 cm Height: 6.0 cm
Weight:	1.35 kg
Noise classification:	Class 0 (no noise at all)

### **Scope of delivery:**

- 1 x controller
- 1 x user manual
- 1 x external mains adapter
- 2 x USB cable
- 2 x mounting bracket
- 4 x screw