

## OMNITRONIC MP-350P PA Mixing Amplifier

PA mixing amplifier with audio player, IR remote control, 350 W RMS

Art. No.: 80709645

GTIN: 4026397504019



**List price: 605.71 €**

incl. 19% VAT.

### Features:

- SD card slot and USB port
- Folder navigation and repeat functions (1, All)
- 3 microphone inputs (6.3 mm jack, unbal.) with separate level controls
- Microphone input 3 with adjustable priority circuit
- 3 line inputs (stereo RCA) with separate level controls
- 1 line output (stereo RCA)
- Chime, switchable
- Treble and bass control for the output signal
- 7-digit LED level meter
- Master control for the output signal
- (19") 48.3 cm rack installation 2 U
- Highly efficient air flow from front to rear
- The device is cooled by temperature-controlled fan
- For application areas such as: Installation; restaurants, bars and hotels; sports centres/gyms

#### audio player

- Control via IR remote control
- LCD display

#### Package contents

- 1 x amplifier, 1 x remote control, 1 x user manual, 1 x battery

### Logistic

EAN / GTIN: 4026397504019

Weight: 14,15 kg

Length: 0.54 m

Width: 0.49 m

Height: 0.18 m

### Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 700,00 W

Protection class:	Protection class I
Output power:	350 W RMS
Power connection:	Fixed power supply cord with safety plug
Device fuse:	5 x 20 mm, T 5 A fuse replaceable
Frequency range:	80 - 14000 Hz
S/N ratio:	>75 dB microphone >85 dB line
THD:	<0,5 % at 1 kHz
Cooling:	Temperature-controlled fan , air flow from front to rear
Impedance:	4-16 ohms; public address systems 100V; Public address systems 70V
Circuitry:	Class AB
Control elements:	Power switch, Master control, tone control, regular talkover
Controls:	Power on/off transient; Overvoltage; short-circuit
Status LED:	Power, fault, master level meter
Connections:	Input: microphone via 1 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Input: microphone via 2 x 6.3 mm plug (unbal.) Input: line via 3 x stereo RCA 0,3 V Output: rec. via 1 x stereo RCA 0,3 V Output: speaker via screw terminal
Channels:	Microphon chanal: 1 x mono via Combination socket (XLR/jack), channel control via rotary dial Microphon chanal: 2 x mono via jack, channel control via rotary dial Input channel: 3 x stereo via RCA, channel control via rotary dial Input channel: via audio player, channel control via rotary dial, mute control Master output: mono, channel control via rotary dial, 2-band tone control EQ
Material:	Metal
Color:	Black
Housing design:	(19") 48.3 cm rack installation 2 U
Dimensions:	Width: 48,3 cm Depth: 40 cm Height: 8,9 cm
Weight:	12,45 kg
Remote control	
Battery:	1 x button cell 3.0 V CR2025 lithium manganese built-in
Audio player	
Control:	IR remote control
Audio player:	USB + SD
Display type:	LCD display
Music format:	MP3, WMA; FLAC, WAV
Number of files:	Max. 999
Available storage media:	USB devices/SD cards max. 32GB (FAT 32)