

OMNITRONIC Amplificateur de mixage MPZ-250.6P

Amplificateur mélangeur mono (système de sonorisation) 6 zones, lecteur audio & télécommande IR, zones commutables, 250 W

Réf. : 80709732

GTIN: 4026397503494



Description:

Enormous reliability with a maximum of flexibility

The Omnitronic MPZ-250.6P ELA mixer amplifier is your reliable partner for ELA sound reinforcement systems. Thanks to its 19" format, it is ideally suited for both mobile and permanent installations.

Outputs for ELA loudspeakers with 70 V and 100 V audio transformers or 4-16- Ohm loudspeakers leave nothing to be desired. In addition, you can also connect a device with line level (e.g. mixing console) to the line output. With 6 mixable inputs you are always flexible. Connect up to 3 microphones and 3 line level devices.

Control your ELA speakers conveniently via the 6 zone outputs of the MPZ-250.6P. They can be switched separately on the front panel. For you, this means the greatest possible adaptability when implementing your sound reinforcement concept.

The MPZ-250.6P also offers you an MP3 player with infrared remote control and blue backlit LCD display. It has both an SD card slot and a USB port. So you can spontaneously and flexibly play music titles from a storage medium of your choice.

Make yourself heard!

The microphone input at the front has an adjustable priority switch. It allows you to make important announcements with automatic, continuously adjustable level reduction of all signals. You can also use the gong to draw attention to your announcement.

Protective functions

A fan protects the interior of your MPZ-250.6P from overheating. In addition to a switch-on delay, it has protection circuits against overvoltage and short-circuits. In these cases, your loudspeakers are electrically isolated from the amplifier. This protects both the MPZ-250.6P and your speakers from damage.

Logistique

EAN / GTIN: 4026397503494

Poids: 12,90 kg

Longueur: 0.54 m

Largeur: 0.49 m

Hauteur: 0.18 m

Caractéristiques:

- Comfortable control of PA speakers via 6-zone technology
- 6 PA zone outputs, independently switchable on the front panel
- Master PA output (70 V and 100 V)
- Output for low-impedance speakers (4-16 ohms)
- SD card slot and USB port
- Folder navigation and repeat functions (1, All)
- 2 rear microphone inputs (6.3 mm jack, unbal.)
- 1 front microphone input (combination XLR/6.3 mm jack, unbal.) with adjustable priority circuit
- All microphone inputs with separate level controls
- 3 line inputs (stereo RCA) with separate level controls
- 1 line output (stereo RCA)
- Chime, switchable
- Treble and bass control for the output signal
- 7-digit LED level meter
- Master control for the output signal
- Protection circuits with LED indication: over current, short circuit, turn-on delay
- Rack installation, brackets detachable
- (19") 48,3 cm installation en rack 2 HE
- L'appareil est refroidi par ventilateur
- Commandé via Télécommande infrarouge

Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	500,00 W
Puissance de sortie:	250 W RMS
Branchement électrique:	Fixe câble d'alimentation à prise contact de protection Tramite
Plage de fréquence:	80 - 16000 Hz
Rapport signal/bruit:	>75 dB microphone >85 dB Line
Distorsion harmonique:	<0,5 % avec 1 kHz
Refroidissement:	Ventilateur
Impédance:	Technologie PA 100 V; 4-16 Ohm
Commande:	Télécommande infrarouge
Lecteur audio:	USB + SD
Sortie de la zone:	6 zones commutables
Commutation:	Class AB
Connexions:	Entrée: microphone via 2 x Prise 6,3 mm (asym.) Entrée: microphone via 1 x câble jack XLR/6,35 mm 3 broches (F) prise combo version encastrable Entrée: Line via 3 x RCA stéréo 0,3 V Sortie: Enceinte via borne à visser Sortie: rec. via 1 x RCA stéréo
Égaliseur:	Master: 1 x régulateur 2 bandes Mono
Format de la musique:	MP3
Nombre de fichiers:	Max. 999
Appareils de stockage appropriés:	Appareils USB/Cartes SD max. 32GB (FAT 32)
Conception du boîtier:	(19") 48,3 cm installation en rack 2 HE
Dimension:	Largeur : 48,3 cm

Profondeur : 38,5 cm

Hauteur : 8,9 cm

Poids: 11,25 kg

Batterie: Pile bouton 3,0 V CR2025 lithium manganèse
intégré

Contenu de la livraison:

- 1 x Mode d'emploi
- 1 x Amplificateur
- 1 x télécommande
- 1 x Batterie