

OMNITRONIC PAP-60 PA Amplifier

Amplificatori ELA, 60 W RMS

Art.n.: 80709804

GTIN: 4026397582055



L'articolo non è più disponibile.

Descrizione :

Reliable amplifier

The Omnitronic PAP-60 ELA mixer amplifier is your reliable partner for ELA sound reinforcement systems. Thanks to its 19" format, it is ideal for both mobile and fixed installations.

Outputs for ELA loudspeakers with 70 V and 100 V audio carriers or 4-16- ? loudspeakers leave nothing to be desired. In addition to a line input, the PAP-60 also offers a loop-through output. Choose between XLR and 6.3 mm jack for both. So you're always flexible.

Protection

A fan protects the interior of your PAP-60 from overheating. In addition to a switch-on delay, it also features protection circuits against overload, short-circuit and DC voltage. In these cases, your loudspeakers are electrically isolated from the amplifier. Both the PAP-60 and your speakers are protected from damage.

Features :

- 1 line input (optionally XLR or 6.3 mm jack)
- 1 feed-through output (optionally XLR or 6.3 mm jack)
- 70 V, 100 V or 4-16 ohms operation
- Master control
- LED indicators for power, signal, clip and fault
- Protective circuits: over load, short circuit, turn-on delay, over heating, DC offset protection
- Load detection and power control
- Rack installation
- Montaggio su rack (19") 48,3 cm 2 U

Logistica

EAN / GTIN: 4026397582055

Peso : 9,60 kg

Lunghezza : 0.54 m

Larghezza : 0.47 m

Altezza : 0.18 m

Dati tecnici :

Alimentazione elettrica:	230 V AC, 50 Hz
Potenza in uscita:	60 W RMS
Allacciamento elettrico:	Pavimento cavo di alimentazione con spina di protezione
Intervallo di frequenza:	60 - 16000 Hz
Rapporto segnale-rumore:	>90 dB line
Distorsione armonica totale:	<0,5 % a 1 kHz
Impedenza:	ELA tecnica 100 V; 4-16 Ohm
Commutazione:	Class AB
Circuito di protezione:	Avvio graduale; surriscaldamento; sovraccarico; Cortocircuito; Tensione continua
LED di stato:	Segnale, power, Fault, clip
Collegamenti:	Ingresso: line via 1 x Presa jack (mono) da 6,3 mm versione da incasso Ingresso: line via 1 x XLR a 3 poli 0,8 V Uscita: line via 1 x Presa jack (mono) da 6,3 mm versione da incasso Uscita: line via 1 x XLR a 3 poli
Struttura della custodia:	Montaggio su rack (19") 48,3 cm 2 U
Misure:	Larghezza: 48,3 cm Profondità: 38,5 cm Altezza: 8,9 cm
Peso:	7,90 kg

Contenuto della confezione:

1 x Amplificatori
1 x Manuale d'uso