

OMNITRONIC HRS-1202FX FX mixer

12-channel home-recording mixer with delay effect

Art.n.: 10040207

GTIN: 4026397262841



L'articolo non è più disponibile.

Features :

- Low noise 12-channel Mic/Line-mixer
- 4 mono inputs with XLR sockets, +48V Phantom-power and balanced line
- 4 stereo inputs with balanced 6.3 mm jack sockets
- Stereo inputs can also be operated mono
- 3-band EQ for all mono inputs
- Adjustable delay effect and effects display
- FX send control per channel for internal FX processor and/or as external send
- Peak-LED per mono input
- Main mix output plus separate phones and stereo CD/tape output
- CD/tape input assignable to main mix or phones output
- 60-mm high-quality faders

Logistica

EAN / GTIN: 4026397262841

Peso : 2,90 kg

Lunghezza : 0.34 m

Larghezza : 0.32 m

Altezza : 0.10 m

Dati tecnici :

Potenza totale installata:	25,00 W
Misure:	Larghezza: 24,5 cm Profondità: 22 cm Altezza: 4,3 cm
Peso:	2,40 kg
Power supply:	2 x 12 V AC, 50 Hz via included power unit
Inputs:	

4 mono	XLR
4 stereo	balanced 6.3 mm jacks
1 Tape In	RCA
Outputs:	
1 Master-Out	balanced 6.3 mm jacks
1 Aux Send:	balanced 6.3 mm jacks
1 Tape Out	RCA
1 Phones	balanced 6.3 mm jacks
1 Rec	RCA
Frequency range:	
Microphone:	10-60000 Hz, ±3 dB
Mono:	10-60000 Hz, ±3 dB
Stereo:	10-55000 Hz, ±3 dB
Distortion:	0.01 %
S/N-ratio:	112 dB
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Dimensions (W x D x H):	245 x 220 x 43 mm

Contenuto della confezione:
