

OMNITRONIC LH-115 Personal Monitor Mixer

Monitor mixer for studio and stage applications

Art.n.: 10355115

GTIN: 4026397318555



L'articolo non è più disponibile.

Descrizione :

The LH-115 provides the opportunity to perfectly record your voice recordings: Take your microphone signal and send it to the LH-115. With one or two headphones you now can now tap the signal and send it, unaltered, to your computer. From there again you can send another signal, background music for example, back to the mixer. Now you can speak sort of on the music and with the level control you are able to easily set the volume of the microphone signal. On your monitor signal you can thus hear the mix the way you prefer it for recording. And due to its small size, it's the ideal partner on the way.

Logistica

EAN / GTIN: 4026397318555

Peso : 0,73 kg

Lunghezza : 0.23 m

Larghezza : 0.13 m

Altezza : 0.08 m

Features :

- Connects a microphone and a further audio source for monitoring
- 1 microphone input via balanced XLR connector with level control
- 1 feed-through output (XLR, bal.)
- 1 aux input via 6.3 mm jack with level control
- 2 headphone outputs via 6.3 mm jacks
- Operation via supplied power unit

Dati tecnici :

Alimentazione elettrica: 12V 150 mA

Potenza totale installata: 2,00 W

Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite connettore cavo (M) versione da incasso cavo di alimentazione con alimentatore a spina (in dotazione)
Intervallo di frequenza:	50 - 20000 Hz
Rapporto segnale-rumore:	>90 dB
Impedenza:	Uscita: 10 Ohm
Gain:	Microfono 50 dB Line 20 dB
Misure:	Larghezza: 11,3 cm Profondità: 4 cm Altezza: 9 cm
Peso:	0,70 kg

Contenuto della confezione: