

OMNITRONIC TRM-202MK2 2-Channel Rotary Mixer

Mixer rotativo a 2 canali con isolatore di frequenza a 3 bande per DJ

Art.n.: 10355921

GTIN: 4026397541816



L'articolo non è più disponibile.

Features :

- Classic rotary mixer with 2 input channels and integrated 3-band frequency isolator for DJs
- Gain control, 2-way equalizer (Highs/Lows) and phono/line switching per channel
- Dedicated boost and kill cut
- Kill cut feature allows DJs to completely remove low, mid and high frequencies for amazing mixing
- Vintage ALPS potentiometers (Blue Velvet RK27)
- High-grade components ensure long life and excellent sound quality
- DJ microphone input with separate level control
- Prefader listening to input channels and the master output via adjustable headphones output, with cue mix/split function
- 10-digit stereo LED level meter and master level control
- Booth output with separate level control
- Inputs: 4 x line and 2 x phono (RCA L/R), DJ microphone (XLR) and headphones (jack)
- Outputs: master and booth (XLR/RCA L/R), record (stereo RCA)
- Operation via supplied power unit

Logistica

EAN / GTIN: 4026397541816

Peso : 3,54 kg

Lunghezza : 0.45 m

Larghezza : 0.24 m

Altezza : 0.14 m

Dati tecnici :

Misure:	Larghezza: 23,5 cm
	Profondità: 19 cm
	Altezza: 9,5 cm
Peso:	2,87 kg
Power supply:	100-240 V AC, 50/60 Hz

	via supplied power unit
Power consumption:	10 W
Gain:	
Line:	20 dB
Phono:	60-75 dB
Mic:	44 dB
Max. output level:	22 dBu
Frequency range:	
Line:	20-20000 Hz
Phono:	40-18000 Hz
Mic:	20-20000 Hz
S/R ratio:	
Line:	85 dB
Phono:	77 dB
Mic:	80 dB
THD:	
Line:	<0.03 %
Phono:	<0.1 %
Frequency isolator:	
Lows:	20 Hz to 300 Hz
Mids:	300 Hz to 4 kHz
Highs:	4 kHz to 20 kHz
Inputs:	
LINE:	RCA L/R
PHONO:	RCA L/R
DJ microphone:	XLR
Outputs:	
MASTER:	XLR/RCA L/R
BOOTH:	XLR/RCA L/R
REC:	RCA L/R
Headphones output:	6.3 mm jack (min. 32 ohms)
Dimensions (W x D x H):	235 x 190 x 95 mm

Contenuto della confezione: