

OMNITRONIC DEQ-231 Digital EQ 2x31-bands

2 x equalizzatore grafico a 31 bande

Art.n.: 10356120

GTIN: 4026397177749



L'articolo non è più disponibile.

Features :

- Gain control in 0.5 dB steps up to 16 dB
- 24 Bit dual DSP
- 48 kHz sampling rate Sigma-Delta, A/D, D/A converter
- Integrated digital Noise Gate
- 100 programs can be memorized via battery backup
- Left/right copying function
- Lock function
- MIDI control possible
- Rack installation, 1 U

Logistica

EAN / GTIN: 4026397177749

Peso : 2,90 kg

Lunghezza : 0.52 m

Larghezza : 0.25 m

Altezza : 0.09 m

Dati tecnici :

Alimentazione elettrica:	115/230 V AC, 50/60 Hz
Potenza totale installata:	10,00 W
Equalizzatore:	2 x equalizzatore grafico a 31 bande
Misure:	Larghezza: 48,3 cm Profondità: 15,2 cm Altezza: 4,45 cm
Peso:	2,00 kg
Inputs:	XLR or balanced 6.3 mm jack
Nominal Operating Level:	-20 dB to +4 dB

Max. input level:	+16 dB at +4 dB nominal level, +2 dB at -20 dB nominal level
Input impedance:	40 ohms balanced, 20 ohms unbalanced
Outputs:	XLR or balanced 6.3 mm jack
Max. output level:	+16 dB at +4 dB nominal level, +2 dB at -20 dB nominal level
Output impedance:	66 ohms balanced, 33 ohms unbalanced
Frequency range:	20-20000 Hz
Distortion:	0.06 %
S/N-ratio:	98 dB, 20-20000 Hz
Crosstalk:	-95 dB, 20-20000 Hz
MIDI-Interface:	5-pin DIN-socket IN/OUT/THRU
Converters:	24-bit Sigma-Delta, 64/128-times oversampling
Sampling rate:	48 kHz
Dimensions (W x D x H):	482 x 152 x 45 mm

Contenuto della confezione: