

OMNITRONIC FX-001 FX processor

Digital 24-Bit stereo multi-effects processor

Art.n.: 10356710

GTIN: 4026397306255



L'articolo non è più disponibile.

Descrizione :

Enhance your music productions with the OMNITRONIC FX processors FX-001 and FX-003! The FX-001 is a dedicated and intuitive stereo multi-effects processor that adds 16 striking effects in 24-bit quality to your set-up. The FX-001 offers 2 channels, provided with level controls and a bypass switch which allows for direct comparison between the original and the processed signal. The unit is intended for rack use.

Logistica

EAN / GTIN: 4026397306255

Peso : 2,60 kg

Lunghezza : 0.55 m

Larghezza : 0.20 m

Altezza : 0.08 m

Features :

- Dedicated 2-channel effects processor for studio and stage applications
- 16 striking effect algorithms, including vocal removal, various reverbs and delays, chorus, flanger rotary speaker and multi-effects
- Intuitive effects selector with LEDs indicating the selected effect
- Adjustable output level
- Inputs and output via balanced XLR connectors and 6.3 mm jacks
- Rack installation, 1 U

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 10,00 W

Intervallo di frequenza: 20 - 20000 Hz

Misure: Larghezza: 48,3 cm

Profondità: 12 cm

	Altezza: 4,45 cm
Peso:	2 kg
S/N ratio:	>90 dB
THD:	0.05%
Crosstalk:	>80 dB, -3 dB
Gain:	-- to +6 dB
Input impedance:	10/20 kohms (unbal./bal.)
Output impedance:	300/150 kohms (unbal./bal.)
Connection:	6.5 mm jack (unbal.), 3-pin XLR (bal.)
Dimensions (W x D x H):	483 x 120 x 46 mm

Contenuto della confezione: