

## OMNITRONIC AR-212A Active 2-way speaker

Active 2-way speaker system for PA and DJ applications, 550 W max.

Art.n.: 11038840

GTIN: 4026397477764



### Features :

- Active full-range system with class D circuitry
- 2-channel power amplifier with integrated active crossover network
- 2-way system, 550 W max.
- 2 x 30 cm subwoofer in bassreflex cabinet
- 12 cm titanium driver system
- Mic and line inputs (XLR/6.3 mm jack) with separate level controls
- Master control with 2-band EQ
- Parallel line output for linking further active speaker systems
- Limiter and speaker switch-on delay
- MDF enclosure with scratch-resistant lacquer surface, impact-resistant steel grille
- Protection against short-circuit and overheat
- For mobile live and DJ applications

### Logistica

EAN / GTIN: 4026397477764

Peso : 39,00 kg

Lunghezza : 0.51 m

Larghezza : 0.46 m

Altezza : 0.98 m

Merci voluminose

### Dati tecnici :

Alimentazione elettrica: 115/230 V AC, 50/60 Hz

Potenza totale installata: 650,00 W

Intervallo di frequenza: 40 - 20000 Hz

Misure: Larghezza: 90 cm

Profondità: 41 cm

Altezza: 38,5 cm

Peso: 34,80 kg

|                         |                                             |
|-------------------------|---------------------------------------------|
| LF amplifier:           | 500 W max.                                  |
| HF amplifier:           | 50 W max.                                   |
| Components:             | 2 x 30 cm woofer (12"), 11.5 cm horn (4.5") |
| Line input:             | combination XLR/6.3 mm jack                 |
| Microphone input:       | combination XLR/6.3 mm jack                 |
| Line output:            | XLR (parallel output)                       |
| Dimensions (H x W x D): | 900 x 410 x 385 mm                          |

### **Contenuto della confezione:**

---