

OMNITRONIC BR-115 Pocket receiver set

Multifrequency pocket receiver set

Art.n.: 13062000

GTIN: 4026397139754



L'articolo non è più disponibile.

Features :

- Set includes multifrequency receiver and mini ear phones
- Can be used for in-ear applications
- 16 UHF frequencies (800.100-813.000 MHz) via DIP switches selectable
- LED display for power supply
- Level control
- Audio output via 3.5 mm mono jack socket for mono earphones
- Power supply via 2 x 1.5 V mignon batteries (type AA) (not supplied)
- A wireless microphone or a belt transmitter with lavalier microphone or headset microphone can be ordered separately

Logistica

EAN / GTIN: 4026397139754

Peso : 0,22 kg

Lunghezza : 0.21 m

Larghezza : 0.07 m

Altezza : 0.06 m

Dati tecnici :

Misure:	Larghezza: 7 cm Profondità: 2,5 cm Altezza: 10,6 cm
Antenna:	Detachable
System:	Non-diversity, one channel
Carrier frequency:	UHF 800.100-813.000 MHz (16 ch.) 800.875, 801.375, 802.375, 803.125, 803.875, 804.500, 805.125, 805.875, 806.625, 807.375, 807.875, 808.375, 809.125, 810.250, 810.875, 811.875 MHz

Frequency stability:	±0.005 %
T.H.D.:	<1 % at 1 kHz
Tone signal:	32.768 kHz
S/N-ratio:	>94 dB at 48 kHz deviation
Input sensitivity:	8 dB
Selectivity:	>50 dB
Dynamic range:	>96 dB
Modulation method:	FM-frequency modulation
Coverage:	>30 m (with line-of-sight)
Frequency range:	50-15000 Hz (±3 dB)
Audio output:	3.5 mm mono jack socket
Power supply:	2 mignon batteries (type AA)
Current consumption:	approx. 110 mA
Battery life:	max. 12 hours
Dimensions (L x W x H):	106 x 70 x 25 mm
Weight:	100 g

Contenuto della confezione:
