

FUTURELIGHT DMH-150 LED Moving Head

High performance LED moving head with 150 W COB LED

Art.n.: 51841970

GTIN: 4026397474534



Features :

- Equipped with a 150 W COB LED - comparable to a 575 W discharge lamp
- With integrated wireless receiver for WDMX operation (Wireless Solution - made in Sweden)
- 21, 23 or 24 DMX channels selectable (up to software version 1.1.00)
- 14, 16, 21 or 24 DMX channels selectable (from software version 1.1.01)
- Effect wheel with rotating 3-facet prism and 8-facet prism and frost filter
- Color wheel with 8 different dichroic color filters plus white
- Rainbow effect with adjustable speed in both directions
- Gobo wheel with 7 rotating gobos plus open
- All gobos can be interchanged
- Slot-in gobo system for exchanging gobos without tools
- With gobo shake function
- Gobo wheel 2 with 7 static gobos plus open
- Exact positioning via 16 bit PAN/TILT movement resolution
- Motorized focus
- Autofocus
- Steplessly adjustable iris
- Dimmer
- Strobe effect with adjustable speed
- Random strobe effect
- Automatic position correction
- PAN angle switchable between 540° and 630°
- Sound-controlled via built-in microphone
- Switch-mode power supply
- Automatic power supply adaption between 100 and 240 Volts without power selector
- Control board with graphic LCD display and foil-keyboard for adjusting the DMX-starting address, PAN/TILT reverse, reset

Logistica

EAN / GTIN: 4026397474534

Peso : 16,15 kg

Lunghezza : 0.52 m

Larghezza : 0.43 m

Altezza : 0.36 m

- DMX-controlled operation or stand-alone operation with Master/Slave function
- The scenes can be modified via the Control Board or via an external controller and loaded into the memory
- Number of scenes can be changed individually
- Software upload by optional accessories via DMX link
- Power connection via Neutrik PowerCon jack and included power cable
- Feed-through output allows to power another device
- After every 8 device the fixtures must have a renewed connection with the power mains
- DMX control via every standard DMX controller
- Può funzionare in modalità 21 CH DMX
- Controllabile via controllo della musica via microfono; DMX; RDM

Dati tecnici :

Alimentazione elettrica:	100-240 V AC, 50/60 Hz
Potenza totale installata:	210 W
Movimento oscillatorio TILT massimo:	270° posizionamento
Movimento di rotazione PAN massimo:	630° posizionamento
Gobo:	Diametro esterno 27mm Diametro immagine 22mm
Canali DMX:	21
Attivazione:	Controllo della musica via microfono; DMX; RDM
Fixtures disponibili per:	Light Captain
Angolazione del fascio di luce (1/2 picco):	14°
Colore:	Nero
Misure:	Larghezza: 34,3 cm Profondità: 25 cm Altezza: 42,8 cm
Peso:	14,10 kg
DMX channels:	21/23/24 (up to software version 1.1.00)
DMX channels:	14/16/21/24 (from software version 1.1.01)
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
Wireless signal transmission:	2.4 GHz (ISM)
LED type:	Array 150 W
LED number:	1
Beam angle:	14°
Color-wheel:	8 dichroic filters plus open
Static gobo-wheel:	7 gobos and open
Rotating gobo-wheel:	7 gobos and open
Outside diameter of the gobos:	27 mm
Image diameter of the gobos:	22 mm
Maximum PAN-movement:	630°
Maximum TILT-movement:	270°
Dimensions (L x W x H):	343 x 250 x 428 mm

Contenuto della confezione:
