

## EUROLITE freeDMX Wi-Fi Interface

USB DMX interface with Wi-Fi module - for EUROLITE Light'J app

Art.n.: 51860125

GTIN: 4026397506587



**L'articolo non è più disponibile.**

### Features :

- DMX interface with integrated Wi-Fi module for wireless control of DMX devices
- freeDMX allows control of DMX devices through smartphones or tablet PCs more flexible than ever - right now true for Eurolite KLS and Hybrids
- For mobile iOS and Android devices
- Download matching apps from the App Store and Google Play
- Applicable as USB DMX interface for controlling DMX devices with a computer
- Supports various DMX software applications
- Fully supported by FreeStyler as of version 3.37 (freeware)
- Input or output of 512 DMX channels
- Windows XP, Vista, 7 and 8, Linux OLA-OpenDMX.net
- 3-pin Neutrik XLR connectors for DMX IN/DMX OUT
- USB 2.0 port
- Status LEDs for Wi-Fi, USB, DMX IN and DMX OUT
- Supports firmware updates
- Driver and firmware updater available for download at [www.eurolite.de](http://www.eurolite.de)
- Powered via included PSU

### Logistica

EAN / GTIN: 4026397506587

Peso : 0,26 kg

Lunghezza : 0.16 m

Larghezza : 0.12 m

Altezza : 0.06 m

### Dati tecnici :

Misure:

Larghezza: 9,8 cm

Profondità: 8,8 cm

Altezza: 5,2 cm

Power supply: 5 V DC, 1.2 A

|                           |                                                             |
|---------------------------|-------------------------------------------------------------|
|                           | via included PSU                                            |
| Wi-Fi standard:           | IEEE 802.11g/b/n                                            |
| Frequency range:          | 2.4 GHz range (ISM), 11 channels                            |
| Übertragungstyp:          | DDSS/OFDM                                                   |
| Data rate:                | 1-11 Mbps (802.11b), 6-54 Mbps (802.11g)                    |
| Antenna:                  | 2 dBi                                                       |
| DMX512 output:            | 1 universe (512 channels)                                   |
| DMX connectors:           | 3-pin XLR mounting socket, 3-pin XLR mounting plug, Neutrik |
| USB port:                 | USB 2.0, type B                                             |
| Dimensions (w/o antenna): | L 98 x W 88 x H 52 mm                                       |
| Weight:                   | 350 g                                                       |

### **Contenuto della confezione:**