

EUROLITE LED PC-Control 512

Lighting control software with USB interface to create professional shows

Art.n.: 51860150

GTIN: 4026397420029



L'articolo non è più disponibile.

Descrizione :

LED PC-Control is the ideal DMX512 software for all DJ and Architectural applications or small/medium-sized projects. It manages all LED technology-based equipment and can control any type of standard DMX appliance. The software is the most user friendly and affordable solution for DMX lighting control.

Features :

- Graphic and user-friendly live board for touchscreens and smartphones
- Remotely trigger scenes and programs via Wi-Fi with your smartphone or instantly change RGB colors of your LED lights and much more
- Automatic program generator with X-Pan, Y-Tilt and RGB effects
- Graphic patch editor for DMX fixture addressing
- Quick fixture profile editor with 3000 files (libraries) included
- Advanced Matrix editor to allow all LED configurations
- Multiple menu languages (e.g. French, English, German)
- Full RGB (W/A) color and dimmer management and rendering
- Graphic 2D edition of fixtures
- Colors, dimmer, speed, black out and pause can be managed in live mode
- Fade-in time between programs and scenes
- Multiple program triggers
- DMX output speed signal can be configured for perfect DMX line stability and full compatibility with any electronic fixtures (Mab, Break, Delay, frequency 1 to 45 Hz)
- Durable aluminum housing with mounting flange
- Può inviare fino a 512 canali DMX
- Controllabile via DMX; SmartBoard DMX App
- The device can be connected via USB to the PC in connection with LED PC-Control 512

Logistica

EAN / GTIN: 4026397420029

Peso : 0,32 kg

Lunghezza : 0.20 m

Larghezza : 0.14 m

Altezza : 0.06 m

- Compatible with Win XP, Win Vista, Win 7, OS X 10,3 o superiore
- Per maggiori informazioni su questo prodotto, consultare "Download" nella scheda tecnica

Dati tecnici :

Alimentazione elettrica:	100-240 V AC, 50/60 Hz 5V DC 500 mA
Potenza totale installata:	1 W
Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite Micro USB (F) versione da incasso cavo di alimentazione per collegamento alla rete USB A (in dotazione)
Canali DMX:	Uscita 512
Uscita DMX:	XLR (F) a 3 poli versione da incasso
Attivazione:	DMX; SmartBoard DMX App
Collegamento USB:	USB 2.0, type mini USB (F) versione da incasso
Colore:	Nero
PC connect:	LED PC-Control 512 via USB
Misure:	Larghezza: 7 cm Profondità: 9 cm Altezza: 4,5 cm
Peso:	0,22 kg
Sistema operativo:	Win XP, Win Vista, Win 7, OS X 10,3 o superiore

Contenuto della confezione:

1 x Dispositivo
1 x alimentatore esterno
1 x Cavo USB
1 x CD
1 x telecomando
1 x Pila