

EUROLITE LED SDR-8 Beam Effect

RGBW beam effect with 2 separately tiltable bars and 8 beams

Art.n.: 51918666

GTIN: 4026397595130



Features :

- TILT movement for each LED bar separately and steplessly adjustable
- Equipped with eight 3 W LEDs: 2 x red, 2x green, 2 x blue and 2 x white
- Each LED can be controlled individually
- 10 or 14 DMX channels selectable
- Compact lightweight
- Functions: colored beams in R, G, B and W, internal programs, dimmer, strobe effect with adjustable speed and random strobe effect, auto mode, sound-control with adjustable sensitivity, Master/Slave operation
- DMX-controlled operation or stand-alone operation with Master/Slave function
- Control board with LED display for adjusting the DMX-starting address, TILT reverse, reset
- Switch-mode power supply for operation between 100 and 240 volts
- Ready for connection with power cord and safety plug
- DMX512 control possible via any commercial DMX controller
- 8 LED 3 W high power R/G/B/W
- Effetto raggianti; Effetto floreale
- Può funzionare in modalità 10; 14 CH DMX
- Controllabile via stand-alone; DMX
- Senza sfarfallio

Logistica

EAN / GTIN: 4026397595130

Peso : 2,54 kg

Lunghezza : 0.32 m

Larghezza : 0.19 m

Altezza : 0.18 m

Dati tecnici :

Alimentazione elettrica: 100-240 V AC, 50/60 Hz

Potenza totale installata: 45 W

Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite dispositivi a freddo (M) versione da incasso cavo di alimentazione con spina di protezione (in dotazione)
Tipo di lampada:	Lampada a LED
Tipo di LED:	8 x 3 W high power R/G/B/W
Canali DMX:	10; 14
Attivazione:	Stand-alone; DMX
Fixtures disponibili per:	LED PC-Control 512
Proiezione:	Senza sfarfallio
Colore della custodia:	Nero
Misure:	Larghezza: 15,5 cm Profondità: 28,5 cm Altezza: 15,5 cm
Peso:	2,28 kg
DMX channels:	10/14
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
LED type:	3 W
LED number:	8 (2 x red, 2 x green, 2 x blue, 2 x white)
Dimensions (L x W x H):	285 x 155 x 155 mm

Contenuto della confezione:

1 x staffa omega