

## OMNITRONIC PA Vol Contr/Prog Select 10W mono wh

Mountable PA program selector and PA volume controller with 24 V emergency priority relay

Art.n.: 80711082

GTIN: 4026397260441



**L'articolo non è più disponibile.**

### Features :

- Combination of PA program selector for 6 signal sources and PA volume controller
- Suitable for 100 V audio technique or other signals
- White plastic front panel and knobs
- Built-in 24 V emergency priority relay
- Attenuation in 11 steps
- Flush mounting in customary 60 mm wall sockets
- Surface mounting with optional PA SF housing
- Mounting depth: 45 mm
- Screw plug connection

### Logistica

EAN / GTIN: 4026397260441

Peso : 0,33 kg

Lunghezza : 0.17 m

Larghezza : 0.10 m

Altezza : 0.07 m

### Dati tecnici :

|                                 |                                                           |
|---------------------------------|-----------------------------------------------------------|
| Relè di ricezione obbligatorio: | 24 V                                                      |
| Capacità di carico:             | Nominale: 10W RMS                                         |
| Intervallo di frequenza:        | 50 - 18000 Hz                                             |
| Ingresso e uscita:              | Mono                                                      |
| Misure:                         | Larghezza: 8 cm<br>Profondità: 6,7 cm<br>Altezza: 15,4 cm |
| Peso:                           | 0,29 kg                                                   |

**Contenuto della confezione:**

---