

## OMNITRONIC PA vol contr/prog select 20W mono bk

Mountable PA program selector and PA volume controller with 24 V emergency priority relay

Art.n.: 80711090

GTIN: 4026397260670



### Features :

- Combination of PA program selector for 6 signal sources and PA volume controller
- Suitable for 100 V audio technique or other signals
- Black plastic front panel and knobs
- Built-in 24 V emergency priority relay
- Attenuazione in 11 livelli
- Connettore a vite
- Montaggio a incasso
- Alloggiamento sopra intonaco (opzionale)

### Logistica

EAN / GTIN: 4026397260670

Peso : 0,33 kg

Lunghezza : 0.17 m

Larghezza : 0.09 m

Altezza : 0.07 m

### Dati tecnici :

|                                 |                                                                 |
|---------------------------------|-----------------------------------------------------------------|
| Relè di ricezione obbligatorio: | 24 V                                                            |
| Capacità di carico:             | Nominale: 20W RMS                                               |
| Intervallo di frequenza:        | 50 - 18000 Hz                                                   |
| Ingresso e uscita:              | Mono                                                            |
| Struttura della custodia:       | Montaggio a incasso<br>Alloggiamento sopra intonaco (opzionale) |
| Misure:                         | Larghezza: 8 cm<br>Profondità: 6,7 cm<br>Altezza: 15,4 cm       |
| Peso:                           | 0,29 kg                                                         |

**Contenuto della confezione:**

---