

OMNITRONIC PM-404F 4-channel DJ Mixer with Filter and Bluetooth

DJ mixer with Bluetooth connectivity and sound filter

Art. No.: 10006867

GTIN: 4026397756869



List price: 320.11 €

incl. 19% VAT.

Features:

- Bluetooth signal routable to channel 1 to 4
- DJ filter LPF/HPF bipolar per channel
- DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
- Crossfader with adjustable curve and reverse function
- Master channel with level and balance control
- 6 line and 2 phono inputs via RCA jacks
- Additional recording output
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Control via Bluetooth
- Bluetooth: operating range up to 20m
- Desktop console housing

Logistic

EAN / GTIN: 4026397756869

Weight: 3,50 kg

Length: 0.39 m

Width: 0.29 m

Height: 0.14 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	15 W
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>75 dB

THD:	<0.1 % at 1 kHz
DJ filter:	Per channel: LPF/HPF bipolar,
Control:	Bluetooth
Bluetooth device name:	PM-404F
Range:	Bluetooth: range up to 20m
Carrier frequency:	2.4 GHz
Housing color:	Black matte
Crosstalk:	>60 dB
Control elements:	Power switch, Master control, level control per channel, Input sensitivity switch, source selector; tone control, talkover, crossfader selector switch, crossfader, connect; cue mix function, Crossfade curve control, crossfade reverse switch, balancecontrol
Status LED:	Power, master level meter, channel level meter, CUE, pairing
Connections:	<p>Input: line via 6 x stereo RCA</p> <p>Input: phono via 2 x stereo RCA</p> <p>Input: microphone via 1 x 3-pin XLR (F) mounting version</p> <p>Input: antenna via 1 x SMA (F) mounting version</p> <p>Input: Earthing connection via 2 x screw terminal</p> <p>Output: master via 2 x 3-pin XLR (M) mounting version</p> <p>Output: master via 1 x stereo RCA</p> <p>Output: rec. via 1 x stereo RCA</p> <p>Output: booth via 1 x stereo RCA</p> <p>Output: booth via 2 x 3-pin XLR (M) mounting version</p> <p>Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version</p> <p>Output: headphones via 1 x 3.5 mm jack (stereo) mounting version</p>
Channels:	<p>Input channel: 2 x stereo with Line-Phono-Bluetooth switch via RCA or Bluetooth, channel control via 60mm fader, 2-band tone control EQ, source selector, gain control, CUE switch, crossfader selector switch, LPF/HPF bipolar</p> <p>Input channel: 2 x stereo with Line-Line-Bluetooth switch via RCA or Bluetooth, channel control via 60mm fader, 2-band tone control EQ, source selector, gain control, CUE switch, crossfader selector switch, LPF/HPF bipolar</p> <p>Microphone channel: 1 x mono via XLR, channel control via rotary dial, 2-band tone control EQ, talkover switch, gain control</p> <p>Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol</p> <p>Booth output: 1 x stereo via XLR or RCA, channel control via rotary dial</p> <p>Rec. output: 1 x stereo via RCA, channel control via rotary dial</p> <p>Headphones output: 2 x stereo via jack, channel control via rotary dial</p>
Material:	Metal
Housing design:	Desktop console housing
Dimensions:	Width: 24 cm

Depth: 33.8 cm

Height: 11 cm

Weight:

2.85 kg

Scope of delivery:

- 1 x mixer
- 1 x power cord
- 1 x antenna
- 1 x RCA cable
- 1 x user manual
- 1 x declaration of conformity