

OMNITRONIC EM-650B MK2 Entertainment Mixer

Multifunctional 5+2-channel mixer with 3 zones, black

Art. No.: 10007113 GTIN: 4026397714326











List price: 474.81 €

incl. 19% VAT.

Features:

- 5 input channels with recessed gain controls on the rear panel, signal LED and smooth channel fadors
- 3 adjustable master outputs with 3-way equalizer and 10-digit stereo LED level meter
- (19") 48.3 cm rack installation 2 U
- For application areas such as: Installation; restaurants, bars and hotels; clubs/dancing school Package contents
- 1 x mixer, 1 x user manual, 1 x power cord, 1 x RCA cable

Logistic

EAN / GTIN: 4026397714326

Weight: 3,46 kg Length: 0.50 m Width: 0.14 m Heigth: 0.18 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Protection class:	Protection class II
Power connection:	Power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>60 dB line
	>70 dB phono
THD:	Line/phono <0,02 % at 1 kHz
Gain:	Microphone 52 dB
	Line 17 dB
	Phono 53 dB
Housing color:	Black

Zone output:	3 adjustable zones
Control elements:	Power switch, regular talkover, source selector
Status LED:	Signal, chanal level meter, master level meter, peak, chanal source; CUE, talkover, ON AIR, routing
Connections:	Input: microphone via 2 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version)
	Input: line/phono via 2 x stereo RCA
	Input: line via 8 x stereo RCA
	Output: master via 3 x 3-pin XLR
	Output: master via 3 x stereo RCA
	Output: rec. via 2 x stereo RCA
	Output: headphones via 1 x 6.3-mm-jack (bal.)
Channels:	Input chanel: 2 x stereo with line-line/phono switch via RCA, channel control via fader, 3-band tone control EQ, routing master bus switch, gain control, source selector, CUE switch
	Input chanel: 3 x stereo with line-line switch via RCA, channel control via fader, routing master bus switch, gain control, source selector, CUE switch
	Microphon chanal: 2 x mono via Combination socket (XLR/jack), channel control via rotary dial, ON AIR switch, routing master bus switch, talkover switch
	Master output: 3 x stereo via XLR or RCA, channel control via rotary dial, 3-band tone control EQ
	Rec. output: 1 x stereo via RCA, routing master bus switch
	Headphones output: 1 x stereo via jack, channel control via rotary dial, cue mix function
Housing design:	(19") 48.3 cm rack installation 2 U
Dimensions:	Width: 48,3 cm
	Depth: 14,8 cm
	Height: 8,9 cm
Weight:	3,10 kg