

OMNITRONIC Set PORTY-8A Drahtlos-PA-System + Bodypack Transmitter incl. Lavalier Mic

GTIN: 4026397739480



Features:

OMNITRONIC PORTY-8A Wireless PA System

Mobile 8" PA system with battery operation, Bluetooth, DSP and wireless microphone

- Powerful sound in an ultra-compact package (114 dB max. SPL)
- Works great as primary PA system, stage monitor and practice amp
- 4-channel mixer
- Stereo Bluetooth link for wireless stereo operation with 2 systems linked together
- UHF receiver unit and matching wireless microphone
- Lightweight plastic housing
- Cordless, flexible and versatile
- Battery operation up to 6.5h at 50% volume; battery operation up to 3.5h at 100% volume
- Integrated automatic charging of the battery and status indicator
- Digital signal processor 96kHz, 24 bit
- DSP presets: FLAT; DJ; LIVE
- Control via Bluetooth
- Bluetooth: operating range up to 20m
- UHF 863 - 865 MHz License-free and approved in Europe
- Dual flange
- Black metal grille
- With tablet holder
- Rugged carrying handle
- Application possibility: Standing; monitoring; on stand
- For application areas such as: Mobile use; mobile djs / entertainer; small rental; product presentations and lectures

Logistic

EAN / GTIN: 4026397739480

Weight: 11,00 kg

Length: 0.00 m

Width: 0.00 m

Heigh: 0.00 m

OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

- Operating range up to 60m
- UHF 863 - 865 MHz License-free and approved in Europe

OMNITRONIC PORTY-8A Transport Bag

- , black

Technical specifications:

Weight:	10.30 kg
---------	----------

OMNITRONIC PORTY-8A Wireless PA System

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	Max. 220 W
Protection class:	Protection class I
Power connection:	Mains input via IEC connector (M) mounting version (provided) Battery/battery pack
Cable length:	1.5 m detachable
Device fuse:	5 x 20 mm, T 3.15 A fuse replaceable
Battery pack type:	1 x lithium ion 22.2 V, 4400 mAh, 97.68 Wh
Battery pack:	Battery operation up to 6.5h at 50% volume Battery operation up to 3.5h at 100% volume Recharging time 4h
Power:	120W RMS
Number of channels:	4
Frequency range:	45 - 18000 Hz
Max. SPL:	114 dB
DSP:	Digital signal processor 96kHz, 24 bit
DSP presets:	FLAT; DJ; LIVE
Control:	Bluetooth
Bluetooth:	Version: 5 with stereo link (TWS)
Bluetooth device name:	OMNITRONIC PORTY-8A
Range:	Bluetooth: range up to 20m
Frequency band:	UHF 863 - 865 MHz
Housing color:	Black
Attachment system:	Dual flange: Ø 35mm
Circuitry:	Class D
Control elements:	Power switch, Input sensitivity switch, Master control, level control per channel, echo effect control; connect

Connections:	Input: mic/line via 3 x 3-pin XLR/6.35mm jack (F) combination socket (mounting version) Input: line via RCA (F) mounting version Input: line via 3.5 mm jack (stereo) mounting version Output: line via 3-pin XLR (M) mounting version
Channels:	Input channel: 3 x mono with Mic-Line-Hi.Z. switch via Combination socket (XLR/jack), channel control via rotary dial, 2-band tone control EQ
Input channels:	1 x stereo via RCA or jack plug or Bluetooth, channel control via rotary dial
Speaker:	Woofer 8" with ferrit magnet 8 x compression tweeter highs 1.35" with ferrit magnet
Type of speaker:	Wireless PA system
Carrying handle:	1 pc/pcs
Material:	Plastic
Dimensions:	Width: 29 cm Depth: 26.3 cm Height: 39.3 cm
Weight:	8.65 kg

OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

Cable length:	0.9 m detachable
Range:	Range up to 60m
Frequency band:	UHF 863 - 865 MHz
Carrier frequency:	863.1 MHz
RF power output:	10 mW
Color:	Black
Weight:	0.13 kg

OMNITRONIC PORTY-8A Transport Bag

Color:	Black
Weight:	0.65 kg

Scope of delivery:

1 x OMNITRONIC PORTY-8A Wireless PA System

1 x compact cabinet speaker
 1 x microphone
 1 x power cord
 1 x user manual
 1 x declaration of conformity
 2 x battery
 1 x battery pack

1 x OMNITRONIC PORTY-8A Bodypack + Lavalier Microphone 863.1 MHz

1 x transmitter
 1 x microphone
 2 x battery

1 x user manual
1 x declaration of conformity

1 x OMNITRONIC PORTY-8A Transport Bag

1 x bag
1 x strap