

EUROLITE LED PAR-30 COB RGB 30W bk

PAR spot with 30 W COB LED (RGB) & adjustable beam angle (15°/28°)

Art. No.: 41607200

GTIN: 4026397460476



The article is no longer in our assortment.

Features:

- Equipped with one powerful RGB 30 W COB LED
- Functions: static colors, RGB color mixture, internal programs, dimmer and strobe settings via DMX, Master/Slave operation
- Operable in stand-alone mode or via DMX
- Beam angle 15° with Fresnel lens - 28° without
- Comfortable addressing and setting via Control Board with LED display and three operating buttons
- Adjustable microphone sensitivity via Control Board
- With color filter frame and Fresnel lens
- Easy installation
- Locking possibility at the mounting bracket
- Ready for connection via power cord with safety plug
- Delivery includes lens
- Available in silver or in black
- 1 powerful LED 30 W COB (chip-on-board) 3in1 TCL RGB (homogenous color mix)
- Strobe effect
- Control via DMX; sound to light via microphone
- Preprogrammed in Light J; LED PC-Control 512; EASY SHOW 1; LED EASY OPERATOR 4x4; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE
- With a beam angle of 28°

Package contents

- 1 x spotlight, 1 x user manual, 1 x lens

Logistic

EAN / GTIN: 4026397460476

Weight: 1,73 kg

Length: 0.20 m

Width: 0.20 m

Height: 0.34 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	30 W
IP classification:	IP20
Power connection:	Fixed power supply cord with safety plug
Lamp type:	LED lamp
LED type:	1 x 30 W COB (chip-on-board) 3in1 TCL RGB (homogenous color mix)
DMX channels:	3; 5
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; sound to light via microphone
Preprogrammed in:	Light´J; LED PC-Control 512; EASY SHOW 1; LED EASY OPERATOR 4x4; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE
Beam angle:	28°
Beam angle (1/2 peak):	28° With fresnell 15°
Housing color:	Black
Dimensions:	Width: 15,5 cm Depth: 21 cm Height: 21,5 cm
Weight:	1,47 kg
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting