

EUROLITE LED Strip 4in1 Zone RF Receiver

Extension controller with 4 x 6A for RGB/W and dual white

Art. No.: 50531145

GTIN: 4026397659832



The article is no longer in our assortment.

Features:

- Easy paring to the basic kit via remote control
  - Any number of controllers possible in 4 zones
  - Memory function saves last setting when switching off
- Package contents**
- 1 x device, 1 x user manual, 1 x declaration of conformity, 2 x screw

Logistic

EAN / GTIN: 4026397659832  
Weight: 0,14 kg  
Length: 0.17 m  
Width: 0.05 m  
Heigh: 0.03 m

Technical specifications:

|                    |                                                                                                   |
|--------------------|---------------------------------------------------------------------------------------------------|
| Power supply:      | 12/24V DC                                                                                         |
| Power consumption: | Max. 288 W 12 V DC<br>Max. 576 W 24 V DC<br>72 W 12 V DC per channal<br>144 W 24 V DC per channal |
| Output current:    | Max. 4 x 6 A per channal                                                                          |
| Power connection:  | Via screw terminal                                                                                |
| Power output:      | Screw terminal                                                                                    |
| Carrier frequency: | 2,4 GHz                                                                                           |
| Dimensions:        | Length: 16 cm<br>Width: 4,6 cm<br>Height: 2,5 cm                                                  |
| Weight:            | 0,11 kg                                                                                           |