

ANTARI Z-380 Fazer

Extremely compact fazer with adjustable output volume & DMX

Art. No.: 51702674

GTIN: 4719850651961



Features:

- Extremely compact fazer with high output
- Produces fine, translucent haze without nebulizing the room at the same time
- Ideal for accentuating light and laser beams
- Combines the reliability of a fog machine with the extremely silent operation of a haze machine
- Control via integrated DMX interface or control module with LCD screen
- Adjustable timer with interval, duration and output volume
- Continuous output with adjustable fan speed and output volume via additional rotary controls
- Self-cleaning function extends lifespan
- Operates on standard waterbased fluid
- Integrated DMX interface (functions: output volume and fan speed, synchronous control possible)
- Intelligent DMX functions: when a DMX signal is received, the Z-380 turns on and starts heating up automatically, when the DMX signal is off, it starts the self-cleaning process and then goes into standby mode
- Z-3 cable remote control available as accessory
- Short warm-up time
- Operates on water-based fluid
- Control via wired remote control (optional); stand-alone; DMX

Logistic

EAN / GTIN: 4719850651961

Weight: 9,25 kg

Length: 0.38 m

Width: 0.33 m

Height: 0.34 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 1500 W

Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Warm-up time:	Approx. 1.5 min
Tank capacity:	1.2 l water-based fluid
Fluid consumption:	Approx. 6 ml/min
DMX channels:	1; 2
DMX input:	1 x 3-pin XLR (M) mounting version 1 x 5-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version 1 x 5-pin XLR (F) mounting version
Control:	Wired remote control (optional); stand-alone; DMX
Housing color:	Grey
Color:	Grey
Dimensions:	Width: 24.8 cm Depth: 32.8 cm Height: 26.5 cm
Weight:	8.30 kg

Scope of delivery:

- 1 x device
- 1 x user manual
- 1 x power cord
- 1 x mounting bracket
- 2 x knurled screw
- 2 x screw
- 1 x container
- 1 x tube