

EUROLITE FX Shot Control 4

4-channel control system for confetti, streamer & CO2 effects devices

Art. No.: 51707820

GTIN: 4026397751178



List price: 296.31 €

incl. 19% VAT.

Description:

The 4-channel control system FX SHOT 4 is ideal for triggering a wide range of special effects devices, including confetti and streamer launchers and CO2 effects. The device has a key switch with status indicator and red trigger switches. Additional safety switches in the channels prevent accidental triggering. The FX SHOT 4 provides P-Con terminals for all connections.

Logistic

EAN / GTIN: 4026397751178

Weight: 3,40 kg

Length: 0.33 m

Width: 0.24 m

Height: 0.17 m

Features:

- 4 separate channels with red trigger switch and safety switch
- Desktop console housing
- Control via plug and play
- For application areas such as: Carnival

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	< 1 W
IP classification:	IP20
Protection class:	Protection class I
Power connection:	Mains input via P-Con (blue), mounting version power supply cord with safety plug (provided)
Power output:	4 x P-Con (gray), mounting version fused

Device fuse:	5 x 20 mm, F 8 A fuse replaceable
Power output fuse per channel:	5 x 20 mm, F 2 A fuse replaceable
Control:	Plug and play
Housing color:	Black matte
Connections:	Output: 4 x
Material:	Metal, painted
Housing design:	Desktop console housing
Dimensions:	Length: 28 cm
	Width: 19 cm
	Height: 12 cm
Weight:	3.03 kg

Scope of delivery:

- 1 x device
- 1 x power cord
- 1 x user manual
- 2 x key