

FUTURELIGHT WDS-G4 TX Wireless-DMX-Transceiver

Wireless DMX system 2.4 GHz - compact transceiver with W-DMX unit by Wireless Solution

Art. No.: 51834022

GTIN: 4026397588958



Features:

- Wireless transmission of DMX data
- Switching between transmitter and receiver
- Compatible with Wireless Solution W-DMX systems
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- AFHSS technology ensures interference-free operation also alongside other DMX transmitters and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Simultaneous operation of up to 6 transmitters, thus control of 6 DMX universes (3072 DMX channels) possible
- 1 to 512 receivers can be controlled by each transmitter
- Plug & Play: quick and easy setup with one operating button
- LED indication for operation and functions
- DMX input and output, 3-pin XLR
- Truss attachment option
- 2.4 GHz - license-free worldwide
- Can receive and process up to 512 DMX channels
- Can transmit up to 512 DMX channels
- Control via DMX; W-DMX by wireless solution
- Operating range up to 500m with line-of-sight
- 2.4 GHz license-free worldwide
- Up to 6 transmitters can be operated in parallel without interference
- Ultra-low latency

Logistic

EAN / GTIN: 4026397588958

Weight: 1,10 kg

Length: 0.21 m

Width: 0.17 m

Height: 0.10 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	3 W
Power connection:	Mains input via P-Con (blue), mounting version power supply cord with safety plug (provided)
DMX channels:	Input 512 Output 512
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; W-DMX by wireless solution
Range:	Range up to 500m with line-of-sight
Frequency band:	2.4 GHz
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
Latency:	< 5 ms
Modulation:	AFHSS
Color:	Black
Dimensions:	Width: 14.5 cm Depth: 10 cm Height: 5.8 cm
Weight:	0.93 kg

Scope of delivery:

- 1 x device
- 1 x power cord
- 1 x fixation clip
- 1 x user manual
- 1 x declaration of conformity
- 1 x antenna