

EUROLITE freeDMX PRO 512 Wi-Fi Interface

Wi-Fi DMX interface for apps & programs like Light Captain

Art. No.: 51860131

GTIN: 4026397696592



Features:

- Wi-Fi DMX interface for wireless lighting control from your tablet or PC
- Receives the control signals via the network and transmits them to the DMX line via cable
- Works with iOS and Android devices
- The apps' online fixture library is continuously updated and already includes more than 300 Eurolite and Futurelight fixtures - easily add new ones via the fixture profile editor
- Control via DMX; Light'J app; Wi-Fi; Light Captain App; QuickDMX via USB (optional)
- Configuration via integrated webserver
- Access point and infrastructure mode
- Internal memory for 1 DMX scene
- DMX feed-through and merge capability
- Can transmit up to 512 DMX channels
- Mounting kits for racks, desks and truss systems available as an option
- Operating range up to 60m in the open air
- Operating range up to 30m in buildings
- 2.4 GHz license-free worldwide
- Multicolor TFT display
- Built with NEUTRIK connector
- The device can be connected via RJ-45 etherCON (F) mounting version to the PC in connection with f.e. FreeStyler, DMXControl 3, PC_DIMMER, Lightkey (MAC)
- Made in Germany
- Silent operation
- For application areas such as: Clubs/dancing school; wedding/gala/events; stage; theater; mobile djs / entertainer; Trade fair and shop fitting; rental; video and photography

Logistic

EAN / GTIN: 4026397696592

Weight: 0,83 kg

Length: 0.33 m

Width: 0.23 m

Height: 0.06 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz 5V DC 1000 mA
Wi-Fi:	Standard: IEEE 802.11 b/g/n
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Network connection:	Protocol: Art-Net 3 via RJ-45 etherCON (F) mounting version, 10 Mbit/s Standard: IEEE 802.3u
Control:	DMX; Light´J app; Wi-Fi; Light Captain App; QuickDMX via USB (optional)
Range:	Range up to 60m in the open air Range up to 30m in buildings
Frequency band:	2.4 GHz
Antenna gain:	2 dBi
Display type:	Multicolor TFT display
USB port:	Type C, 1 A
Use of brands:	Built with NEUTRIK connector
Color:	Black
PC connect:	F.e. FreeStyler, DMXControl 3, PC_DIMMER, Lightkey (MAC) via RJ-45 etherCON (F) mounting version
Dimensions:	Width: 20 cm Depth: 8 cm Height: 4.1 cm
Noise classification:	Class 0 (no noise at all)

Scope of delivery:

- 1 x device
- 1 x external mains adapter
- 1 x USB cable
- 1 x user manual
- 1 x antenna