

EUROLITE FD-36+1 DMX Dimmer Panel

Basic DMX controller for 36 channels with master fader

Art. No.: 70063835

GTIN: 4026397749991



List price: 117.81 €

incl. 19% VAT.

Features:

- Basic DMX controller for convenient operation of light effect units with DMX512 interface (e.g. spotlights and dimmers)
- Simply connect and operate, requires no extensive programming
- 12 channel faders for adjusting the DMX values in 3 groups
- 1 master fader
- Compact design
- Can transmit up to 36 DMX channels
- Desktop console housing

Logistic

EAN / GTIN: 4026397749991

Weight: 1,83 kg

Length: 0.37 m

Width: 0.21 m

Height: 0.10 m

Technical specifications:

| | |
|--------------------|--|
| Power supply: | 100-240 V AC, 50/60 Hz 5V DC 75 mA Or 9V DC 75 mA |
| Power consumption: | < 1 W |
| Power connection: | Mains input via USB C (W) mounting version power supply cord for USB A mains connection included |
| Battery: | 1 x 9.0 V E block 6LR61 alkaline manganese (not included) |
| DMX channels: | Output 36 |

| | |
|-----------------|---|
| DMX output: | 1 x 3-pin XLR (F) mounting version |
| Control: | DMX; QuickDMX |
| Housing color: | Black matte |
| Display type: | 2 x 3 digit 7-segment LED display |
| Material: | Metal, painted |
| Housing design: | Desktop console housing |
| Dimensions: | Length: 34 cm Width: 14 cm Height: 6 cm |
| Weight: | 1.55 kg |

Scope of delivery:

1 x controller
1 x user manual
1 x external mains adapter
1 x USB cable