

EUROLITE FD-36+1 DMX Dimmer Panel

Basic DMX controller for 36 channels with master fader

Art. No.: 70063835

GTIN: 4026397749991



Features:

- Basic DMX controller for convenient operation of light effect units with DMX512 interface (e.g. spotlights and dimmers)
- Simply connect and operate, requires no extensive programming
- 12 channel faders for adjusting the DMX values in 3 groups
- 1 master fader
- Compact design
- Can transmit up to 36 DMX channels
- Desktop console housing

Logistic

EAN / GTIN: 4026397749991

Weight: 1,83 kg

Length: 0.37 m

Width: 0.21 m

Height: 0.10 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz 5V DC 75 mA Or 9V DC 75 mA
Power consumption:	< 1 W
Power connection:	Mains input via USB C (W) mounting version power supply cord for USB A mains connection included
Battery:	1 x 9.0 V E block 6LR61 alkaline manganese (not included)
DMX channels:	Output 36

DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; QuickDMX
Housing color:	Black matte
Display type:	2 x 3 digit 7-segment LED display
Material:	Metal, painted
Housing design:	Desktop console housing
Dimensions:	Length: 34 cm Width: 14 cm Height: 6 cm
Weight:	1.55 kg

Scope of delivery:

1 x controller
1 x user manual
1 x external mains adapter
1 x USB cable