



Description:

Despite its unimposingly elegant looks, the INTUPAK VRE11 is a powerful and versatile user frontend for INTUSONIC's RS-485 enabled audio control systems. It fits standard wall box sizes with minimal depth and hence can be mounted right where it is needed -- in the room to be controlled. A standard CAT network cable is sufficient for connections; no additional power supply is required. Due to its daisy-chaining possibilities, more than one unit can be installed in a room, with the last operated one setting the system, and those settings being replicated on all VRE11 panels as well as the connected main unit. A local audio feed is possible as well, via the provided 3.5mm jack. For even better convenience, the VRE11 also sports an infrared remote control receiver and comes with an IRB44 remote control right out of the box. The VRE11 is compatible with the VLA42 control node and other RS-485 enabled INTUSONIC audio systems.

Logistique

EAN / GTIN: 5060502923271
Poids: 0,31 kg
Longueur: 0.11 m
Largeur: 0.10 m
Hauteur: 0.07 m

Caractéristiques:

- Commandé via Télécommande infrarouge
- Montage encastré
- Vous trouverez de plus amples informations sur ce produit dans la rubrique « Téléchargements » de la fiche technique

Données techniques:

Commande:	Télécommande infrarouge
Profondeur de pose:	30 mm
Conception du boîtier:	Montage encastré

Dimension:	Largeur : 8,6 cm
	Profondeur : 8,6 cm
	Hauteur : 4,2 cm
Poids:	0,26 kg

Contenu de la livraison:

1 x Appareil
1 x Mode d'emploi
1 x télécommande
1 x Batterie
6 x vis
1 x Diaphragme