

OMNITRONIC PM-211 DJ mixer

Mixer per DJ a 2 canali

Art.n.: 10006870

GTIN: 4026397467130



Features :

- 2 input channels with gain control and phono/line switching
- DJ microphone input with talkover selector, level and tone control
- Adjustable front aux input for portable music players (e.g. iPod)
- Pre-fader listening (CUE) to the input channels via adjustable headphones output, with cue mix control
- Crossfader for crossfading between both channels
- 5-digit stereo LED level meter, switchable between master and PFL signal
- Additional recording output
- Operation via supplied power unit

Logistica

EAN / GTIN: 4026397467130

Peso : 1,40 kg

Lunghezza : 0.30 m

Larghezza : 0.20 m

Altezza : 0.10 m

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 3,00 W

Intervallo di frequenza: 20 - 20000 Hz

Misure: Larghezza: 18 cm
Profondità: 14 cm
Altezza: 6,5 cm

Peso: 1,15 kg

via supplied power unit

Inputs:

Line/phono:	2 x stereo RCA
Aux:	3.5 mm stereo jack
DJ microphone:	6.3 mm jack, unbal.
Outputs:	
Master:	stereo RCA
Record:	stereo RCA
Headphones output:	6.3 mm stereo jack (min. 32 ohms)
S/N ratio:	>75 dB
Distortion:	<0.07 %
Dimensions (L x W x H):	180 x 140 x 65 mm

Contenuto della confezione:
