

FUTURELIGHT CP-512 MST Controller 16 bit

Universal DMX controller

Art.n.: 51834299

GTIN: 4026397280326



L'articolo non è più disponibile.

Features :

- 512 control channels for 16 projectors with up to 32 channels
- 16-bit resolution for fine Pan/Tilt movements
- Projector library with up to 255 entries
- 64 programs
- 64 records
- 64 preset scenes, 64 preset macros
- 10 selectable languages
- Mirror movement direction can be inverted
- Copy function for scenes, programs and records
- 99 chasers definable, one chaser per program
- Blackout function
- Sound control via built-in microphone or audio input
- Security code operation
- Operating hour meter
- USB port for firmware updates (available in the download section)
- Rack installation with 6 U
- Può inviare fino a 512 canali DMX
- Controllabile via DMX

Logistica

EAN / GTIN: 4026397280326

Peso : 5,40 kg

Lunghezza : 0.56 m

Larghezza : 0.34 m

Altezza : 0.21 m

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 6,00 W

Grado di protezione: IP20

Canali DMX:	Uscita 512
Attivazione:	DMX
Colore della custodia:	Nero
Colore:	Nero
Misure:	Larghezza: 48,3 cm Profondità: 17,6 cm Altezza: 8,9 cm
Peso:	4,50 kg
	via 12 V DC, 500 mA power unit included in the delivery
Number of control channels:	512
Sound-input:	6.3 mm stereo Jack
Audio-sensitivity:	0.3-1 V
DMX512 output:	3-pin XLR connector
Free chasers:	64
Dimensions (LxHxD):	483 x 265 x 83 mm
	Rack installation with 6 u
Minimum mounting depth:	90 mm