

EUROLITE DTB-405 4-channel Dimmerbar 5A

Dimmer bar for chaser or DMX operation

Art.n.: 70064420

GTIN: 4026397108057



Features :

- Makes the installation of your lighting system really easy
- Installed directly on the stand or crossbeam
- With 4 spot connections
- Outputs via 4 safety sockets
- Can be used either as a 4-channel chaser controller or a DMX dimmer pack
- 6 different operation modes
- 16 pre-programmed chaser patterns
- Chaser direction can be inverted
- Chaser speed controllable or sound-controlled
- Sound control via built-in microphone
- Remote control via optional footswitch
- Only for professional use

Dispositivo

- Senza fili, flessibile e versatile

Logistica

EAN / GTIN: 4026397108057

Peso : 6,00 kg

Lunghezza : 1.35 m

Larghezza : 0.21 m

Altezza : 0.27 m

Merci voluminose

Dati tecnici :

| | |
|--------------------------|--|
| Alimentazione elettrica: | 230 V AC, 50 Hz |
| Corrente in uscita: | Max. 5 A per canale |
| Misure: | Larghezza: 130 cm Profondità: 10 cm Altezza: 10,5 cm |
| Peso: | 5,05 kg |

| | |
|----------------------------------|---------------------------------|
| Tipo di batteria: | 1 x nickel metal hydride 3,6 V, |
| Max. power output: | 3680 W |
| Max. total current: | 16 A |
| Max. output/channel: | 1150 W |
| Max. current/channel: | 5 A |
| Fuse: | F 6.3 A, 250 V |
| Maximum load per fixation point: | 4 kg |
| Max. spaced braceload: | 16 kg |
| Max. centered braceload: | 25 kg |
| TV spigot: | D = 28 mm |
| Dimensions (L x W x H): | 1300 x 100 x 105 mm |

Contenuto della confezione:

1 x Dispositivo