

OMNITRONIC PA Vol Contr/Prog Select 20W mono wh

Mountable PA program selector and PA volume controller with 24 V emergency priority relay

Art.n.: 80711083

GTIN: 4026397260601



L'articolo non è più disponibile.

Features :

- Combination of PA program selector for 6 signal sources and PA volume controller
- Suitable for 100 V audio technique or other signals
- White plastic front panel and knobs
- Built-in 24 V emergency priority relay
- Attenuation in 11 steps
- Flush mounting in customary 60 mm wall sockets
- Surface mounting with optional PA SF housing
- Mounting depth: 45 mm
- Screw plug connection

Logistica

EAN / GTIN: 4026397260601

Peso : 0,34 kg

Lunghezza : 0.17 m

Larghezza : 0.10 m

Altezza : 0.07 m

Dati tecnici :

Relè di ricezione obbligatorio:	24 V
Capacità di carico:	Nominale: 20W RMS
Intervallo di frequenza:	50 - 18000 Hz
Ingresso e uscita:	Mono
Misure:	Larghezza: 8 cm Profondità: 6,7 cm Altezza: 15,4 cm
Peso:	0,30 kg